

XG-80PB01

Wired Panic Button



Overview

The XG-80PB01 Wired Panic Button is designed for immediate activation in emergency situations or as a reliable exit button for access control systems. It provides flexible installation options and comes in durable housing with customizable labels.

Its large, easy-to-press button ensures quick response times, while the bright LED indicator provides clear visual confirmation of activation. The device is compatible with a variety of alarm and access control systems, making it a versatile addition to any security setup.

Key Feature

High Load Capacity:	Supports a load current of up to 1.25A, ensuring reliable operation during emergencies.
Durable Construction:	Made from high-quality ABS material, the panic button is robust and resistant to physical damage.
Key Reset Mechanism:	After activation, the button can be easily reset using the provided key, preventing accidental reactivation and ensuring secure operation.
Wide Application:	Suitable for various settings, including nursing homes, banks, jewelry stores, and homes, where immediate response is critical.
Reliable Performance:	Operates at a working voltage of 12V DC with a switch withstand voltage of 250V DC, ensuring consistent performance under different conditions.

Emergency Activation

Provides instant alert for quick response during emergencies.

Durable ABS Material

Built to last with robust and impact-resistant ABS construction.

High Load Capacity

Supports up to 1.25A load current, ensuring reliable operation.

Specification

Model Number:	XG-80PB01
Housing:	ABS, grey/white available
Carrying Current:	0.3 A
Working Voltage:	12V DC
Switch Withstand Voltage:	250V DC
Connection Type:	Wired
Reset Method:	Key Reset
Output:	NO. & N.C. terminals
Dimension:	54×54×32(mm)